

Model		VM-5011A	VM-5011B
Input range		0 - 500m/s <sup>2</sup>	
Measuring range of frequency	Accerelation	-	10 Hz - 10 kHz
	Envelope accerelation	10 Hz - 1 kHz BFP: 500 - 10 kHz	-
	Velocity	10 Hz - 1 kHz	
Measuring range	Accerelation	-	10/25/50/100 m/s <sup>2</sup> rms
	Envelope accerelation	10/25/50/100 m/s <sup>2</sup> rms	-
	Velocity	10/25/50/100 mm/s rms	
DC output	Accerelation	-	4-20 mA or DC0-10 V
	Envelope accerelation	4-20 mA or DC0-10 V	-
	Velocity	4-20 mA or DC0-10 V	
AC output	Accerelation	-	0-1 Vrms
	Envelope accerelation	0-1 Vrms	-
	Velocity	0-1 Vrms	
Sensor waveform output		Depends on sensor voltage sensitivity	
Operating temperature/humidity range		0 to 50°C、95%RH or less (without freezing or condensing)	
Power supply of converter		DC24 V ±10%	
Size		22.6 (W) x 99 (H) x113.6 (D) mm (Excluding protrusions)	
Mass		Approx.150 g	